

(10±5) seconds to (6±2) minutes. Position (-) indicates the minimum length.

Ambient light adjustment: sign (-) indicates that the load will be turned on only at night and (+) indicates it will be switched on during daytime and night.

- Refit the plastic lampshade and lock it with plastic screw nut.
- Switch on the power. If the TIME control is set at position (-) and not receiving any effective signal, the road-light will turn off within 60 seconds, then the sensor enters into automatic detection state.



Warning

In order to avoid false triggering, it should not be positioned close to heat sources as air-conditioner, flue and strong electromagnetic disturbance area.

Note

- The unit is for indoor use only. Don't install it on the moist ceiling or wall.
- Not suitable for use with dimmer switch.
- Disconnect the power first while opening cover or cleaning.
- Don't damage the lens of the sensor. There are no serviceable components inside.

DESCRIPTION:

LAMBARIO-LAMBADOX-WHITE-WITHSENSOR-6400K-LED WALL LAMP

Users' Manual

MODEL: LH01-01030

Brief introduction

PIR lamp can detect the infrared rays released by human body motion within the detection area. The lamp will auto light up when detect moving person when the body moving into the detection area . The lamp will auto turn off when the body leaves the sensible area. It can identify day or night automatically and intelligently.

This model also have emergency function. When electrical power is off, The emergency LED will continue on via rechargeable battery. When electrical power is on again, the rechargeable battery will be charged up.

Specifications

Power Source: 220~240V/AC, 50~60Hz

Detect range: 120°×360°

Detect distance: 6m (MAX, 22~24°C)

Duration time: 10±5s-6±2m (adjustable)

Ambient light: <5Lux-daylight (adjustable)

Rated load: 12W

LED quantity: 60pcs SMD2835 + 6pcs SMD5050 for emergency

Luminance: 800LM

Work temperature: -10°C~+40°C

Installation

- Make sure that the power is off.
- Unscrew the plastic screw nut and remove the plastic lampshade.
- Mark the mounting position on the ceiling with the bottom plate, drill holes in the marked position and fill them with dilatable plastic screws (supplied), fix the bottom plate to the selected position with supplied screws.
- Connect the power cable to AC power wiring terminal through the rubber ring in the center of the bottom plate. Connect the battery cable to DC power wiring terminal.
- Adjust “TIME” and “LUX”:

Duration time adjustment: it can be set according to the consumer desire from